



**Functional
Devices, Inc.**

Bulletin B526

• RIBM2401SB 393017C

LED ON = RELAY ACTIVATED

Functional Devices, Inc.
101 Commerce Drive
Sharpsville, IN 46068
Phone: (800) 888-5538

functionaldevices.com

COIL RATINGS


INPUT ISOLATED
FROM OUTPUT
47 mA @ 30 Vdc
83 mA @ 24 Vac, 50-60 Hz
47 mA @ 120 Vac, 50-60 Hz

CONTACT RATINGS

20A Resistive @ 277 Vac
1 HP @ 120 Vac
2 HP @ 277 Vac
20 A Ball. @ 277 Vac (N/O)
10 A Ball. @ 277 Vac (N/C)
10 A Tung. @ 120 Vac (N/O)
770 VA Pilot @ 120 Vac
1110 VA Pilot @ 277 Vac

Connect Yellow Jumper
Wire to N/O or N/C

N/O N/C
○ ○



SIGNALING



LISTED
13CY
15M6

TYPE F, G, EM

For use with
Smoke Control System
General Signaling
Equip. NM

CONTACTS

Relay Contacts

Not Used

COIL



Comm



24Vac/dc



120Vac

